



NOTES:

1. SETS ARE FACTORY WIRED FOR BRIDGED RINGING SERVICE. RINGER CONNECTIONS PROVIDE FOR RINGING ON LINE 1. FOR RINGING ON LINE 2, CONNECT (BL) STRAP FROM A OF NETWORK AND (BK) RINGER LEAD TO TERMINALS 3 AND 4 RESPECTIVELY.
 2. TO SILENCE RINGER PERMANENTLY, CONNECT (BK) RINGER LEAD TO K OF NETWORK.
 3. CURRENT PRODUCTION SETS DO NOT HAVE CONTACTS j-k AND ASSOCIATED (O) AND (BL) LEADS.
 4. LINE SWITCH SEQUENCE, HANDSET REMOVED:

bc - MAKES	ab - BREAKS
de - MAKES	fg - BREAKS
 5. WHEN 4228K NETWORK IS PROVIDED, TERMINALS 10, 11, AND 12 ON THE TERMINAL STRIP SHALL BE REPLACED BY TERMINALS L2, G, AND LI, RESPECTIVELY ON THE NETWORK. (SEE NOTE 3)
- * INSULATE AND STORE

Fig. 1—2555B (MD) Telephone Set, Connections